



# Series 0600 Strip-Line™ Header w/Coined Contacts

## FEATURES

- Available with Fork- or Post-style Coined Contacts
- Header to be Cut to Desired Number of Positions Required
- Side-to-side and End-to-end Stackable

## GENERAL SPECIFICATIONS

- **BODY MATERIAL:** Black UL 94V-0 Glass-filled 4/6 Nylon
- **COINED CONTACTS:** Brass, 1/2-hard
- **CONTACT PLATING:** 200μ min. matte Sn plating per ASTM B545-97(2004)e1 over 50μ [1.27μ] min. Ni per QQ-N-290 –OR– 10μ [0.25μ] min. Au per MIL-G-45204 over 50μ [1.27μ] min. Ni per QQ-N-290 –OR– 200μ [5.08μ] min. Sn/Pb 90/10 per MIL-T-10727 over 50μ [1.27μ] min. Ni per QQ-N-290
- **CONTACT CURRENT RATING:** 2 amps
- **OPERATING TEMPERATURE:** 221°F [105°C] for Sn & Sn/Pb plating; 257°F [125°C] for Au plating
- **ACCEPTS LEADS:** up to 0.025 [0.64] dia. leads

## MOUNTING CONSIDERATIONS


- **SUGGESTED PCB HOLE SIZE:** 0.035 ±0.002 [0.89 ± 0.05] dia.



## ORDERING INFORMATION

**XX-0600-X X**

- Plating
  - 0 = Sn
  - 0TL = Sn/Pb
  - 1 = Au
- Pin Style
  - 1 = Fork
  - 2 = Post
- Series
- No. of Pins
  - 1 to 25



"A" = NO. OF PINS PER ROW x 0.100 [2.54]

"B" = (NO. OF PINS PER ROW - 1) x 0.100 [2.54]

ALL DIMENSIONS: INCHES [MILLIMETERS]

ALL TOLERANCES: ±0.005 [0.13] UNLESS OTHERWISE SPECIFIED

FOR SCREW MACHINE CONTACTS, SEE [DATA SHEET 12036](#)

CONSULT FACTORY FOR OTHER SIZES AND CONFIGURATIONS

CUSTOMIZATION: ARIES SPECIALIZES IN CUSTOM DESIGN AND PRODUCTION. SPECIAL MATERIALS, PLATINGS, SIZES, AND CONFIGURATIONS CAN BE FURNISHED, DEPENDING ON QUANTITY.

ARIES RESERVES THE RIGHT TO CHANGE PRODUCT GENERAL SPECIFICATIONS WITHOUT NOTICE

PRINTOUTS OF THIS DOCUMENT MAY BE OUT-OF-DATE AND SHOULD BE CONSIDERED UNCONTROLLED



**ARIES**  
ELECTRONICS, INC.

2609 Bartram Road • Bristol, PA 19007-6810 USA

TEL 215-781-9956 • FAX 215-781-9845

[WWW.ARIESELEC.COM](http://WWW.ARIESELEC.COM) • [INFO@ARIESELEC.COM](mailto:INFO@ARIESELEC.COM)



12034  
Rev. 4.1  
1 of 1

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Aries Electronics:

<a href="#"><u>20-0600-20</u></a>	<a href="#"><u>18-0600-21</u></a>	<a href="#"><u>18-0600-20</u></a>	<a href="#"><u>10-0600-11</u></a>	<a href="#"><u>10-0600-10</u></a>	<a href="#"><u>18-0600-11</u></a>	<a href="#"><u>18-0600-10</u></a>	<a href="#"><u>10-0600-21</u></a>	<a href="#"><u>10-0600-20</u></a>	
<a href="#"><u>14-0600-20</u></a>	<a href="#"><u>14-0600-21</u></a>	<a href="#"><u>14-0600-10</u></a>	<a href="#"><u>14-0600-11</u></a>	<a href="#"><u>12-0600-21</u></a>	<a href="#"><u>12-0600-20</u></a>	<a href="#"><u>12-0600-11</u></a>	<a href="#"><u>12-0600-10</u></a>	<a href="#"><u>16-0600-10</u></a>	<a href="#"><u>16-0600-11</u></a>
<a href="#"><u>16-0600-20</u></a>	<a href="#"><u>16-0600-21</u></a>	<a href="#"><u>17-0600-21</u></a>	<a href="#"><u>17-0600-20</u></a>	<a href="#"><u>17-0600-11</u></a>	<a href="#"><u>17-0600-10</u></a>	<a href="#"><u>13-0600-20</u></a>	<a href="#"><u>13-0600-21</u></a>	<a href="#"><u>13-0600-10</u></a>	<a href="#"><u>13-0600-11</u></a>
<a href="#"><u>19-0600-20</u></a>	<a href="#"><u>19-0600-21</u></a>	<a href="#"><u>11-0600-10</u></a>	<a href="#"><u>11-0600-11</u></a>	<a href="#"><u>19-0600-10</u></a>	<a href="#"><u>19-0600-11</u></a>	<a href="#"><u>11-0600-20</u></a>	<a href="#"><u>11-0600-21</u></a>	<a href="#"><u>20-0600-10</u></a>	<a href="#"><u>20-0600-11</u></a>
<a href="#"><u>15-0600-21</u></a>	<a href="#"><u>15-0600-20</u></a>	<a href="#"><u>15-0600-11</u></a>	<a href="#"><u>15-0600-10</u></a>	<a href="#"><u>22-0600-21</u></a>	<a href="#"><u>22-0600-20</u></a>	<a href="#"><u>22-0600-11</u></a>	<a href="#"><u>22-0600-10</u></a>	<a href="#"><u>25-0600-10</u></a>	<a href="#"><u>25-0600-11</u></a>
<a href="#"><u>20-0600-11</u></a>	<a href="#"><u>20-0600-21</u></a>	<a href="#"><u>24-0600-21</u></a>	<a href="#"><u>24-0600-20</u></a>	<a href="#"><u>24-0600-11</u></a>	<a href="#"><u>24-0600-10</u></a>	<a href="#"><u>25-0600-10</u></a>	<a href="#"><u>25-0600-11</u></a>	<a href="#"><u>23-0600-10</u></a>	<a href="#"><u>23-0600-11</u></a>
<a href="#"><u>25-0600-21</u></a>	<a href="#"><u>21-0600-11</u></a>	<a href="#"><u>21-0600-10</u></a>	<a href="#"><u>21-0600-21</u></a>	<a href="#"><u>21-0600-20</u></a>	<a href="#"><u>23-0600-21</u></a>	<a href="#"><u>23-0600-20</u></a>	<a href="#"><u>23-0600-11</u></a>	<a href="#"><u>23-0600-10</u></a>	<a href="#"><u>04-0600-11</u></a>
<a href="#"><u>02-0600-11</u></a>	<a href="#"><u>02-0600-10</u></a>	<a href="#"><u>02-0600-20</u></a>	<a href="#"><u>02-0600-21</u></a>	<a href="#"><u>06-0600-21</u></a>	<a href="#"><u>06-0600-20</u></a>	<a href="#"><u>06-0600-10</u></a>	<a href="#"><u>06-0600-11</u></a>	<a href="#"><u>09-0600-11</u></a>	<a href="#"><u>09-0600-10</u></a>
<a href="#"><u>04-0600-10</u></a>	<a href="#"><u>04-0600-21</u></a>	<a href="#"><u>04-0600-20</u></a>	<a href="#"><u>08-0600-20</u></a>	<a href="#"><u>08-0600-21</u></a>	<a href="#"><u>08-0600-10</u></a>	<a href="#"><u>08-0600-11</u></a>	<a href="#"><u>05-0600-10</u></a>	<a href="#"><u>05-0600-11</u></a>	<a href="#"><u>05-0600-20</u></a>
<a href="#"><u>01-0600-21</u></a>	<a href="#"><u>01-0600-20</u></a>	<a href="#"><u>01-0600-11</u></a>	<a href="#"><u>01-0600-10</u></a>	<a href="#"><u>09-0600-21</u></a>	<a href="#"><u>09-0600-20</u></a>	<a href="#"><u>07-0600-20</u></a>	<a href="#"><u>07-0600-21</u></a>	<a href="#"><u>07-0600-10</u></a>	<a href="#"><u>07-0600-11</u></a>